



MANUAL CALL POINT TRIPLE POLE FP3



Introducing the latest addition to the FP3 range of Manual Call Points.

As integrated systems become more popular there is a requirement for more sophisticated devices to meet this demand. The FP3/GR/TP has three single change over outputs. This allows the Call Point to signal three separate devices from a single action.



- SW1/SW2 rated at 125/250v AC 12A
- SW3 rated at 125v AC 3A
- Operating voltage 12-24v DC
- Resettable plastic operating element
- Red LED Indicator

For example a **single** pole EDR will drop power to a magnetic lock.

A **double** pole EDR will allow you to drop power to a magnetic lock with one pole and control a local sounder with the second pole.

A **triple** pole EDR will allow you to drop power to a magnetic lock with one pole, control a local sounder with the second pole and operate a security system or access control unit with the third pole.



| FP3/GR/TP | |
|--------------------------|---|
| Operating Element | Resettable (Plastic) |
| Switch Type | 3 x Single pole changeover |
| Operating Voltage | 12-24 volts DC |
| SW1 - SW2 Contact Rating | 12A 125/250v AC |
| SW3 Contact Rating | 3A 125v AC |
| LED Indicator | Red LED with current limiting resistor 12/24 Volt |
| Terminal Type | 2.5mm Insertion type, rated 10A 250V |
| IP Rating | IP44. For internal use only |
| Temperature Range | -10°C to +55°C |
| Materials | Case ABS. Operating elements polycarbonate |



Contact us:

Phone:

Tel: +44(0)151 6061000
Fax: +44(0)151 6061122

Online:

Web: www.cqr.co.uk
Email: info@cqr.co.uk

Address: CQR Fire & Security, 125 Pasture Road, Moreton, Wirral, CH46 4TH, UK.

